

Range Extender Rex



Tech specs

Classification	Radio channel range extender
Maximum connected devices (in a system with one range extender)	Hub, Hub 2 — up to 99 Hub Plus — up to 149
Max number of connected ReX per hub	Hub — 1 Hub Plus — 5 Hub 2 — 5
Jeweller radio technology	<p>Communication range with detectors — up to 1,800 m in an open space</p> <p>Two-way communication between devices</p> <p>Operating frequencies — 868.0 - 868.6 MHz</p> <p>Self-adjusting RF output power — up to 25 mW</p> <p>Block encryption based on AES algorithm</p> <p>Detector polling period — 12–300 s</p> <p>Frequency hopping</p>



QR code for simple connection



SmartBracket mount for quick set up



Mobile application for configuring and testing